

# Mellanox ETH

Zjisteni part numberu a verze firmwaru u Mellanox karet. Potrebujeme mit nainstalovany balicek mstflint

```
# ethtool -i ens4f0np0
driver: mlx5_core
version: 5.5-1.0.3
firmware-version: 14.27.1016 (MT_2420110004)
expansion-rom-version:
bus-info: 0000:10:00.0
supports-statistics: yes
supports-test: yes
supports-eeprom-access: no
supports-register-dump: no
supports-priv-flags: yes

# lspci | grep Mella
10:00.0 Ethernet controller: Mellanox Technologies MT27710 Family
[ConnectX-4 Lx]
10:00.1 Ethernet controller: Mellanox Technologies MT27710 Family
[ConnectX-4 Lx]
81:00.0 Ethernet controller: Mellanox Technologies MT27710 Family
[ConnectX-4 Lx]
81:00.1 Ethernet controller: Mellanox Technologies MT27710 Family
[ConnectX-4 Lx]

# lspci -vv -s 10:00.0 | grep "Part number" -A 3
      [PN] Part number: MCX4121A-XCAT
      [EC] Engineering changes: AJ
      [SN] Serial number: MT2031J10949
      [V0] Vendor specific: PCIeGen3 x8

# mstflint -d 10:00.0 q
Image type:          FS3
FW Version:          14.27.1016
FW Release Date:     27.2.2020
Product Version:     14.27.1016
Rom Info:            type=UEFI version=14.20.19 cpu=AMD64,AARCH64
                    type=PXE version=3.5.901 cpu=AMD64
Description:         UID                               GuidNumber
Base GUID:           0c42a10300eabd04          4
Base MAC:            0c42a1eabd04          4
Image VSD:           N/A
Device VSD:          N/A
PSID:                MT_2420110004
Security Attributes: N/A
```

## Upgrade FW

Podle part number a PSID vybereme konkretni verzi FW na webu NVIDIA. V našem případě je to **Part number: MCX4121A-XCAT** a **PSID: MT\_2420110004**. Vybereme tedy nasledujici firmware:

Version (Current)	OPN	PSID	Download/ Documentation
14.32.1900	MCX4411A-ACAN MCX4131A-GCAT MCX4131A-BCAT MCX4121A-XCHT <b>MCX4121A-XCAS</b> MCX4121A-ACUT MCX4121A-ACHT	<b>MT_2420110004</b>	<b>ConnectX4Lx:</b> <a href="#">fw-ConnectX4Lx-rel-14_32_1900-MCX4121A-XCA_Ax-UEFI-14.25.17-FlexBoot-3.6.502</a> <b>MD5SUM:</b> 06adda309f41dae265387470cae6c880  <b>SHA256:</b> bb86ede3116089043595e3b81ac4d54bbfe7f937090fec9a8d3c9db08164effc  <b>Release Date:</b> 03-September-2024  <b>Documentation:</b> <a href="#">Release Notes</a> <a href="#">EULA</a>

Po stazeni je dobre overit md5 prikazem md5sum a porovnat, jestli sedi s checksumem uvedenym na webu.

```
06adda309f41dae265387470cae6c880 fw-ConnectX4Lx-rel-14_32_1900-MCX4121A-XCA_Ax-UEFI-14.25.17-FlexBoot-3.6.502.bin.zip
```

A nyní můžeme po rozbalení přejít k upgradu FW:

```
# mstflint -d 10:00.0 -i fw-ConnectX4Lx-rel-14_32_1900-MCX4121A-XCA_Ax-UEFI-14.25.17-FlexBoot-3.6.502.bin burn
```

```
Current FW version on flash: 14.27.1016  
New FW version: 14.32.1900
```

```
FSMST_INITIALIZE - OK  
Writing Boot image component - OK  
-I- To load new FW run mstfwreset or reboot machine.
```

```
# mstflint -d 10:00.0 v
```

FS3 failsafe image

```
/0x00800038-0x00801e8b (0x001e54)/ (BOOT2) - OK  
/0x00802000-0x0080201f (0x000020)/ (ITOC_HEADER) - OK  
/0x00804000-0x0081472b (0x01072c)/ (IRON_PREP_CODE) - OK  
/0x00815000-0x008150ff (0x000100)/ (FS3_RESET_INFO) - OK
```

```

/0x00816000-0x00816bff (0x000c00)/ (FW_MAIN_CFG) - OK
/0x00817000-0x008174bf (0x0004c0)/ (FW_BOOT_CFG) - OK
/0x00818000-0x008195ff (0x001600)/ (HW_MAIN_CFG) - OK
/0x0081a000-0x0081a13f (0x000140)/ (HW_BOOT_CFG) - OK
/0x0081b000-0x0081dc7f (0x002c80)/ (PHY_UC_CONSTS) - OK
/0x0081e000-0x0081e13f (0x000140)/ (IMAGE_SIGNATURE_256) - OK
/0x0081f000-0x0081f8ff (0x000900)/ (PUBLIC_KEYS_2048) - OK
/0x00820000-0x0082008f (0x000090)/ (FORBIDDEN_VERSIONS) - OK
/0x00821000-0x0082123f (0x000240)/ (IMAGE_SIGNATURE_512) - OK
/0x00822000-0x008230ff (0x001100)/ (PUBLIC_KEYS_4096) - OK
/0x00824000-0x00873fff (0x050000)/ (FS4_PART_TYPE_PROGRAMMABLE_HW_FW) -

```

OK

```

/0x00874000-0x00925e27 (0x0b1e28)/ (ROM_CODE) - OK
/0x00926000-0x00935fff (0x010000)/ (CRDUMP_MASK_DATA) - OK
/0x00936000-0x009369ff (0x000a00)/ (PHY_UC_CMD) - OK
/0x00937000-0x0094091f (0x009920)/ (PHY_UC_CODE) - OK
/0x00941000-0x0096c457 (0x02b458)/ (PCI_CODE) - OK
/0x0096d000-0x00cbb8bf (0x34e8c0)/ (MAIN_CODE) - OK
/0x00cbc000-0x00cc9cbf (0x00dcc0)/ (PCIE_LINK_CODE) - OK
/0x00cca000-0x00ccae3f (0x000e40)/ (POST_IRON_BOOT_CODE) - OK
/0x00ccb000-0x00ccce0f (0x001e10)/ (UPGRADE_CODE) - OK
/0x00ccd000-0x00ccd3ff (0x000400)/ (IMAGE_INFO) - OK
/0x00ccd400-0x00ccdb6f (0x000770)/ (DBG_FW_INI) - OK
/0x00ccdb70-0x00ccdb77 (0x000008)/ (DBG_FW_PARAMS) - OK
/0x00fa0000-0x00faffff (0x010000)/ (NV_DATA) - CRC IGNORED
/0x00fb0000-0x00fbffff (0x010000)/ (NV_DATA) - CRC IGNORED
/0x00fc0000-0x00fcffff (0x010000)/ (FW_NV_LOG) - CRC IGNORED
/0x00fee000-0x00fee1ff (0x000200)/ (DEV_INFO) - OK
/0x00ff8000-0x00ff813f (0x000140)/ (MFG_INFO) - OK
/0x00ff8140-0x00ff81b7 (0x000078)/ (VPD_R0) - OK

```

-I- FW image verification succeeded. Image is bootable.

```
# mstflint -d 10:00.0 q full
```

```

Image type:          FS3
FW Version:          14.32.1900
FW Version(Running): 14.27.1016
FW Release Date:     25.8.2024
Part Number:         MCX4121A-XCA_Ax
Description:         ConnectX-4 Lx EN network interface card; 10GbE dual-
port SFP28; PCIe3.0 x8; ROHS R6
Product Version:     14.27.1016
Rom Info:            type=UEFI version=14.20.19 cpu=AMD64,AARCH64
                    type=PXE version=3.5.901 cpu=AMD64
Description:         UID                               GuidNumber
Base GUID:           0c42a10300eabd04                          4
Base MAC:            0c42a1eabd04                          4
Image VSD:           N/A
Device VSD:          N/A
PSID:               MT_2420110004
Security Attributes: N/A

```

Default Update Method: fw\_ctrl

Nakonec provedeme reboot stroje.

```
Image type:          FS3
FW Version:          14.32.1900
FW Release Date:     25.8.2024
Product Version:     14.32.1900
Rom Info:            type=UEFI version=14.25.17 cpu=AMD64,AARCH64
                    type=PXE version=3.6.502 cpu=AMD64
Description:         UID                GuidNumber
Base GUID:           0c42a10300eabd04         4
Base MAC:            0c42a1eabd04         4
Image VSD:           N/A
Device VSD:          N/A
PSID:                MT_2420110004
Security Attributes: N/A
```

Cerpano odtud:

- [Firmware Connect-X4](#)

From:  
<https://wiki.spoje.net/> - **SPOJE.NET**

Permanent link:  
<https://wiki.spoje.net/doku.php/howto/hw/mellanox?rev=1736536341>

Last update: **2025/01/10 20:12**

